



### Description

The FlexPower C4, C8 lock controller modules add either 4 or 8 lock control outputs to a FlexPower power supply and are typically supplied as part of a system or purchased as an expansion piece to an existing system.

Each module provides either 4 or 8 access control inputs capable of voltage or dry contact activation.

Each module provides either 4 or 8 lock outputs, each one programmable for fail-safe, fail-secure, dry contact, and fire alarm over ride for egress lock control.

Each lock output is also programmable to either of the two voltages available when used in a FlexPower dual voltage power system.

Each output is supervised for voltage and/or blown fuse with the fault reported to the host power supply.

### Specifications

Parameter	Rating
Lock Outputs	4 / 8
Access Control Inputs	4 / 8
Input Voltage	12 and/or 24 VDC
Input Current	20 Amps
Output Voltage (Jumper Select)	12/24 VDC
Output Current C4/C8	Fused at 3A per output
Output Current C4P/C8P	Class II at 2.5A per output
Fire Alarm Interface	Per Output
Supports follow on modules	Yes

### Features and Functions

#### Flexibility

- ◆ Multiple outputs for direct lock control and additional accessory power distribution modules
- ◆ Colored coded by function configuration jumpers for ease of programming
- ◆ Configurable fail-safe, fail-secure, and dry contact modes of operation
- ◆ Fire Alarm Interface (FAI) when used with an FPO power supply
- ◆ Fault detection and reporting to host power supply
- ◆ FlexConnect® Dual Buss Architecture

#### Output protection

- ◆ C4/C8 ATM style fuse: 3A/per output
- ◆ C4P/C8P Solid state circuit breaker: 2.5A/per output

#### Visual Indicators

- ◆ DC voltage per output (green LED)
- ◆ Fault (yellow LED)

#### Mechanical

- ◆ Multiple modules can be daisy chained to add additional outputs
- ◆ Snap-in style mounting standoffs with fast-on connect cables for easy field installation

#### Lifetime warranty

- ◆ Fiberglass PCB and high efficiency circuit provides less heat generation leading to a longer service life and lower MTBF

### Ordering

Model No.	Mechanical Information
C4 4 output, Fused	Size: 4" x 2.5" x 1.5" Weight: .50 lb.
C4P 4 output, Class 2 Power Limited	
C8 8 output, Fused	Size: 6" x 4 x 1.5" Weight: .75 lb.
C8P 8 output, Class 2 Power Limited	

*Provided with cables and mounting hardware*

### Agency Listings

Product listed for use in  
LifeSafety Power equipment

#### USA

UL 294 UL 1481  
UL 603 UL 2044  
UL 864 UL 2572  
UL 1076  
FCC Part 15, Subpart B  
CSFM Approved

#### CANADA

ULC S318  
ULC S319  
ULC S527  
CSA C22.2 #107.1  
CSA 22.2 #60950

### Lifetime Warranty



**FLEXPOWER Standard Features**

**VSelect®** One single switch for configuring the output between 12 and 24VDC eliminates field errors and allows for the reduction and simplification of service inventory by eliminating the necessity of stocking units in each voltage..

**FlexConnect®** Power supply and accessory board interconnection system uses common mounting footprints, predrilled mounting holes, snap-in standoffs, pluggable wires, and a dual buss distribution architecture to simplify installation and service.

**Reliability+®** FPO power supplies are fully fault protected and feature fiberglass printed circuit boards to protect the electronics from water and other corrosive elements found in industrial settings. High efficiency design promotes low heat generation leading to longer service life.

**GreenSmart®** FlexPower systems are RoHs compliant, lead-free, and meet the latest state, federal and European requirements for energy efficiency.

**Expansion** This module is typically part of an existing system or purchased to expand an existing system.

**Flexibility** This module may also be used to add lock control features to an existing system that currently does not feature these functions.

This module may be added to any existing FlexPower system without restrictive agency listing issues.

**C4/8 Module Programming**

- Each input may be programmed to respond to:
- ◆ Application of voltage between 9 and 33VDC
  - ◆ Removal of voltage between 9 and 33VDC
  - ◆ Normally open dry contact transition
  - ◆ Normally closed dry contact transition

- Each output may be programmed for the following modes:
- ◆ Voltage output from power supply one
  - ◆ Voltage output from power supply two
  - ◆ Fail-safe
  - ◆ Fail-secure
  - ◆ Normally open dry contact
  - ◆ Normally closed dry contact
  - ◆ Fire alarm interface for egress lock control

**JUMPER PROGRAMMING**

Reference Jumper Color

<b>A</b>	RED	FAI
<b>B</b>	BLUE	INVERT input
<b>C&amp;E</b>	BLACK	WET/DRY output
<b>D</b>	YELLOW	V SELECT
<b>F</b>	WHITE	INVERT output

**LifeSafetyPower.com**

(888) 577-2898  
 info@lifesafetypower.com

Specifications subject to change without notice.

© 2014 LifeSafety Power Inc. All rights reserved. LifeSafety Power and FlexPower are registered trademarks of LifeSafety Power Inc. All other trademarks and copyrights are the property of their respective owners.

P01-002A 01/14

**LifeSafety Power, Inc.**  
 750 Tower Road, Unit B  
 Mundelein, IL 60060 USA