



HFX-7004M

KIT W/4 USERS W/MEC. QUADRA AND MINI HF, 2 WIRES



The HFX7004M is our NEW and improved entry level video intercom kit with all the perks of its predecessor along with an updated design and improved technology. The kit includes our NEW 4.3" MINI-HF monitor (4 pcs), along with a power supply & and our NEW Quadra door entry station. Expandable up to 4 door stations.

- NEW INTERIOR MONITOR MODEL MINI HANDSFREE WITH VIVID 4.3" COLOR SCREEN.
- NEW QUADRA EXTERIOR DOOR STATION WITH MECHANICAL BUTTON
- KIT IS EXPANDABLE TO 4 EXTERIOR DOOR STATIONS.
- IMPROVED TOUCH CAPACITIVE TECHNOLOGY FOR INTERIOR STATIONS



HFX-7004M

KIT W/4 USERS W/MEC. QUADRA AND MINI HF, 2 WIRES

KIT PRODUCT



EX-DSME

2-WIRE QUADRA EXTERNAL UNIT

MAIN FEATURES - EX-DSME

Type:	
Type of finish:	Die-cast aluminum
Audio/video system:	Yes
Wall-mounted:	Yes
Camera:	
Type of sensor:	1/4" CMOS
Lens size (inch):	0.08
Diagonal viewing angle (°):	98
Minimum color lighting (lux):	1
Camera orientation:	Yes
Power supply:	
Maximum current absorption (mA):	250
Clamps:	LL RTE COM DO SE- SE+C NC NO
Buttons to call:	Yes
Total buttons:	4
Microphone volume control:	Yes
Loudspeaker volume control:	Yes
Operating temperature (°F):	-13 ÷ 131
IP protection rating (IP code):	IP54
Vandal Resistant rating (IK code):	



EX-7000H

COLOUR HANDS-FREE MINI MONITOR, S2



HFX-7004M

KIT W/4 USERS W/MEC. QUADRA AND MINI HF, 2 WIRES

KIT PRODUCT



1209/4

4 OUTPUT POWER SUPPLY FOR 2-WIRE VIDEO KIT


Power supply for 2-wires video kit, 4 monitor outputs.



HFX-7004M

KIT W/4 USERS W/MEC. QUADRA AND MINI HF, 2 WIRES


ACCESSORIES



4791

Adapter plate for Quadra

Plate allowing installation of the Quadra external unit in 1- and 2-module flush-mounted boxes by Comelit, Bticino and Urmet. Dimensions 137x236 mm



4792

RAIN SHIELD FOR QUADRA ENTRANCE PANEL

Rain shield in painted aluminum for Quadra entrance panel, gray colour. Dimensions (W x H x D): 3.9" x 8.27" x 1.61".



4793MB

BLACK FACEPLATE FOR QUADRA W/BUTTONS

Black faceplate for Quadra entrance panel with mechanical buttons



4793MC

CORTEN FACEPLATE FOR QUADRA W/BUTTONS


Corten colour faceplate for Quadra entrance panel with mechanical buttons



4793MA

ALUMINIUM FACEPLATE FOR QUADRA W/BUTTONS

Aluminium colour faceplate for Quadra entrance panel with mechanical buttons



1217

NAME TAG SHEETS FOR QUADRA ENTRANCE PANEL

The kit contains 10 sheets of adhesive labels for nameplates



HFX-7004M

KIT W/4 USERS W/MEC. QUADRA AND MINI HF, 2 WIRES

ACCESSORIES



1235A

NAMEPLATE LABEL PRINTING SOFTWARE


Dedicated software for the creation and printing of nameplate and information labels for Ikall, Vandalcom, Quadra and 316 Analog entrance panels. Requires use of adhesive labels art.1217, 1218, 1219 or art.1220. This software is available to download free of charge from the Comelit website



6710

BACKPLATE AND DISTRIBUTION TERMINAL FOR MINI MONITOR

Wall-mounting or residential series box backplate for MINI monitor, /BM versions with handset featuring magnetic induction for hearing aid wearers. Also includes riser distribution terminal Art. 1214/2C. Dimensions 145x100x4 mm.



6733W

ADDITIONAL BUTTONS KIT FOR MINI MONITOR, WHITE

Accessory for transforming MINI monitors Art 6700W-/BM and 6701W-/BM into versions with 8 buttons. Includes an 8-button faceplate and an electronic module for activating the buttons, which can be installed quickly without opening up the monitor.



6720

Access. cables external passage for MINI HF. S2

Wall support bracket for handsfree Mini monitor allowing thru-routing of external cables.



6732

DESK BASE FOR HANDSFREE MINI MONITOR

Desk base for desktop conversion of Handsfree Mini monitor. Complete with 1x 2 metre cable with RJ45 connector to connect monitor terminals to the coupler or domestic series socket. Dimensions: 140x190x140mm.



1209

2-WIRE VIDEO KIT POWER SUPPLY UNIT

33 VDC power supply unit with overload and short circuit protection devices. It has two separate continuous outputs: one for external unit and one for the monitor power supply. Input voltage 110-240 VAC. Dimensions: 4.17"x2.44"x3.5" (6 DIN modules).



HFX-7004M

KIT W/4 USERS W/MEC. QUADRA AND MINI HF, 2 WIRES

ACCESSORIES



1229A

ADDITIONAL RINGTONE ACCESSORY. S2

Wall-mounted accessory for additional ringtone for direct connection to 2-wire bus. Allows ringtone selection and adjustment of ringtone volume with privacy function, equipped with dip switches for user code programming, floor door call input terminals and call repeat. Fitted with distribution terminal art. 1214/2C. Dimensions: 125x95x24mm.



1256

ACTUATOR RELAY

Intelligent Simplebus device for controlling a 10 A (12-24 V relay contact) on board. It can be used in Simplebus 1 and Simplebus 2 systems. Depending on the position of the jumper, the device provides six distinct functions: call repetition, activation on porter switchboard call pushbutton, door opening (without external unit), activation on actuator pushbutton, activation on actuator pushbutton with code. For use and programming of the function required, follow the indications given in the technical documentation. If used in mixed audio/video systems, the actuator relay needs terminal art. 1214/2 to be purchased separately. Power supply: 12V AC or 20V DC. Dimensions: 2.6"x3.3"x1.4". (4 DIN modules).



1404

DIGITAL SWITCHING DEVICE. 2-WIRE SYSTEM

Audio/video switching module for Simplebus 2 2-wire digital systems. To be used in systems with more than one entrance. Power supply from bus line. Dimensions: 60x85x35 mm (4 DIN modules).



1405

DIGITAL EXCHANGE 2 QUADRA INPUTS. S2

Audio/video switching module for audio/video kit systems. For use in systems with a maximum of 2 entrances with Quadra series external unit. Power supply from bus line. Dimensions: 35x90x58mm (2 DIN modules).



1409

ACCESSORY FOR REMOTE COLOUR CAMERAS, 2-WIRE SYSTEM

Remote camera module for Simplebus 2 2-wire digital systems. Allows management of up to 3 colour cameras in cyclical sequence from door entry monitors using a dedicated button. 12 Vac or 20 Vdc power supply. Dimensions: 60x85x35 mm (4 DIN modules).