

# JASCO®



## 28170 (ZW3105)

### Z-Wave, Two Outlet Plug-In Smart Dimmer

#### Key Features

- One Z-wave controlled AC outlet for dimmable LED, CFL and incandescent lights
  - Remote ON/OFF and Brightness control via the Z-Wave controller
  - Manual ON/OFF and Brightness control with the top push-button
- One always-on Pass-through Outlet
- Space efficient design
  - Does not block the lower outlet when plugged in to the upper outlet of a duplex wall receptacle. (This assumes that the duplex receptacle is mounted with the ground pin down.)
  - Plugs and cords for connected devices route to the side allowing close placement of furniture
- OTA Updateable
  - Utilizes the Z-Wave Firmware Update Meta Data command class for standardized firmware updates Over the Air
- Z-Wave Plus certified

#### SPECIFICATIONS

Power 120VAC, 60Hz

Signal (Frequency) 908.4/916 MHz

Maximum load for the Z-Wave controlled outlet: 300 W Incandescent / 100W dimmable CFL/LED.

Maximum load for pass-through outlet: 1800W

Total Maximum load for both outlets combined: 15 Amps, 1800W Resistive

Z-Wave controlled outlet is fused @ 5A. This fuse is not user serviceable.

Range: Up to 150 feet line of sight between the Wireless Controller and the closest Z-Wave receiver module.

Operating Temperature Range: 32-104° F (0-40° C)

For indoor use only.

cUL Listed

Complies with FCC and Industry Canada regulations

JASCO Products

10 E. Memorial Rd

Oklahoma City, OK 73114

[www.jascopeproducts.com](http://www.jascopeproducts.com)

[www.easzyzwave.com](http://www.easzyzwave.com)

Z-Wave is a registered US trademark of Sigma Designs

The images, product information and specifications listed in this document are subject to change