

# SX SUPERVISED TRANSMITTERS

## T-90D

Supervised Door/Window Transmitter



## TX-91

2-Button, 3-Channel Handheld Transmitter



## TX-92

3-Button, 6-Channel



## TX-94

5-Button, 15-Channel



- Full RF Supervision
- Tamper and Test Switches
- Test Switch
- Includes Integral Magnet
- Provisions for External Devices
- Includes All Mounting Hardware
- Custom Configurable via Mode Switch and Jumpers

- Unique Top Button Actuator
- Test/Operate LED
- Pocket Clip and Belt Clip Supplied
- Lithium Battery Powered
- Full RF Supervision

### GENERAL SPECIFICATIONS

#### TD-90

<b>Mounting:</b>	snaps into mounting plate (supplied)
<b>Power:</b>	two 3V DL-2032 lithium batteries (supplied); optional - two 3V DL-2450 lithium batteries for extended life
<b>Battery Life:</b>	up to five years with DL-2032 batteries; up to seven years with DL-2450 batteries
<b>Operating Temperature:</b>	32° to 120° F (0° to 49° C)
<b>Frequency:</b>	303.875 MHz
<b>Number of Codes:</b>	16,777,216
<b>Code Setting Method:</b>	factory programmed
<b>Mode Switch Settings:</b>	N/O or N/C DIP switch selectable; fast or slow response DIP switch selectable; glass break selection DIP switch selectable; retransmission delay DIP switch selectable
<b>Jumper Selection:</b>	left reed switch; right reed switch; reed switches disabled; external switch enable

#### TX-91, TX-92, TX-94

<b>Dimensions:</b>	1.6 in L x 0.8 in W x 4.2 in H (41 x 20 x 107 mm)
<b>Power:</b>	two 3V DL-2032 lithium batteries (supplied)
<b>Battery Life:</b>	up to five years
<b>Operating Temperature:</b>	32° to 140° F (0° to 60° C)
<b>Actuation Indication:</b>	LED indicator and tactile feedback
<b>Accessories:</b>	pocket clip and belt clip (supplied)
<b>Frequency:</b>	303.875 MHz
<b>Number of Codes:</b>	16,777,216
<b>Code Setting Method:</b>	factory programmed

### ORDERING

MODEL	PRODUCT NUMBER	DESCRIPTION
T-90D	SST00050D	SX Door/Window Transmitter with Magnet
TX-91	SST00055	2-Button, SX Handheld Transmitter
TX-92	SST00056	3-Button, SX Handheld Transmitter