

4-in-1 HD TVI, CVI, AHD, Analog Wall-Plate Camera

EV-Y5105-N2SQ

The ENFORCER 4-in-1 HD TVI, CVI, AHD, Analog Wall-Plate Camera equipped with Sony STARVIS, that provides high quality color saturation when recording at night. The Wall-plate Camera can be installed inconspicuously in many different locations: doors, walls, car bumpers, gates, entryways, machinery, and many other places.

Features:

- 2.9mm Lens (155° viewing angle)
- 1/2.8" 2MP Sony STARVIS CMOS
- D-WDR (Digital Wide Dynamic Range)
- 2DNR (2D Digital Noise Reduction)
- Vandal-resistant
- Fits in a standard single-gang back box (not included)
- · Adjustable mounting angle
- Each kit includes:
 - Camera
 - Single-gang plate
 - Slimline plate
 - Angled mounting rings





NORE MORE

155° Wide Angle Camera











Specifications:

Model		EV-Y5105-N2SQ
Туре		Wall-Plate Camera
Image sensor		1/2.8" 2MP Sony STARVIS CMOS
Resolution		1080p
Video output format		TVI (Default) / CVI / AHD / Analog
Video output		1.0Vp-p Complex video, 75Ω
Lens		2.9mm
Viewing angle		155°
Minimum illumination		Color: 0.01Lux, BW: 0.001Lux
S/N Ratio		50dB
Operating voltage		12VDC
Current draw		130mA
IP Rating		IP67
Operating temperature		14°~122° F (-10°~50° C)
Dimensions	Camera	1 ⁷ / ₁₆ "xø1 ¹ / ₈ "(36xø28 mm)
	Single-gang plate	2 ³ / ₄ "x4 ¹ / ₂ " (70x114 mm)
	Slimline plate	1 ¹ / ₂ "x4 ¹ / ₂ " (38x114 mm)
Camera body weight		2.8-oz (80g)

Many Ways to Install:

Standard Installation



Protruding Installation



Angled Installation



Back Box Installation



With Plate



Without Plate



SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA, 92606

Phone: (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326 **Website:** www.seco-larm.com **Email:** sales@seco-larm.com

FC (E

Copyright © 2018 SECO-LARM U.S.A, Inc. All rights reserved.

All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.