

Request-to-Exit Plate

SD-7202GC-PEQ Green, 2" square, push-button

Features:

- ▶ Stainless-steel, single-gang message plate.
- Large (2" square), illuminated, momentary push button.
- "PUSH TO EXIT" message can be replaced with "PRESIONE PARA SALIR" message.
- N.O./N.C. contacts rated 10 Amps.

Included:

- "PUSH TO EXIT" and "PRESIONE PARA SALIR" message plates.
- ► Five color-coded, 12-inch, AWG 18 wire leads with easy-to-attach spade lugs for fast installation.
- Stainless-steel single-gang plate.
- Replacement bulb (12V, 1.2W, 15,000-hour life).
- Resistor (150 ohm, 1 Watt).




SD-7202GC-PEQ

Connection Diagram: Green (light bulb) 12V or 24V (requires resistor)* Blue/White (for N.O.) Green/White (for N.C.) Green/White (for N.C.)

*Note: Use 150 ohm, 1 watt resistor on either one of Green wires for 24 volt bulb operation.

Dimensions:





"PRESIONE PARA SALIR" message plate also included

Copyright 2011 SECO-LARM U.S.A., Inc. All rights reserved.

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.



1.949.261.2999 (CA & Int'l) Email: info@seco-larm.com 1.800.662.0800 Fax: 1.949.261.7326 Website: www.seco-larm.com

