Tripp Lite 1111 W. 35th Street Chicago, IL 60609 USA Telephone: 773.869.1234

www.tripplite.com

SmartPro LCD 120V 1500VA 900W Line-Interactive UPS, AVR, 2U Rack/Tower, LCD, USB, DB9 Serial, 8 **Outlets**

MODEL NUMBER: SMART1500LCD











Description

The SMART1500LCD SmartPro LCD 120V, 1500VA/900W Line-Interactive Uninterruptible Power Supply

provides battery backup and AC power protection against blackouts, brownouts, power surges and line noise that can damage electronics or destroy data. Ideal for backing up your desktop computer or audio/visual components, this line-interactive UPS switches to battery backup mode in milliseconds to keep your connected equipment running long enough to save files and shut down safely with no data loss.

Eight NEMA 5-15R outlets protect against surges, as well as provide up to 13 minutes of UPS battery support at half load (450W) and 3.5 minutes of support at full load (900W). Automatic voltage regulation (AVR) corrects severe undervoltages as low as 75V and overvoltages as high as 147V without using any battery power. EMI/RFI noise filtering improves your equipment's performance and prevents damage. A 480-joule surge suppression rating protects your equipment from harmful power surges.

AVR and battery statuses at a glance. Alarm sounds to indicate power loss or low battery. With Tripp Lite's free PowerAlert software (available via free web download), the SMART1500LCD enables safe unattended system shutdown and file saves in case of a prolonged power failure.

Features

Reliable Battery Backup

- Provides 1500VA/900W high-performance power protection for desktop computers, audio/video components, media centers and other electronics
- Supports 50% load (450W) up to 13 minutes and full load (900W) up to 3.5 minutes
- · Audible alarm indicates loss of utility power or low battery

Optimized Outlets

8 NEMA 5-15R outlets provide battery backup and protect against surges or spikes that can harm equipment or data

Automatic Voltage Regulation (AVR)

Highlights

- Supports a half-load (450W) up to 13 min. during power outage
- Supports a full load (900W) up to 3.5 min. during power outage
- Features 8 protected NEMA 5-15R outlets
- · Offers automatic voltage regulation (AVR)
- · LCD screen reports real-time UPS and power status

Package Includes

- SMART1500LCD SmartPro LCD 120V 1500VA/900W Line-Interactive UPS
- USB cable
- DB9 serial cable
- Telephone cable
- Mounting hardware
- Owner's Manual

NEMA 5-15P plug with 6-foot cord connects to any NEMA 5-15R socket. Large rotatable LCD screen with dimmer shows real-time input voltage, overload,



· Corrects undervoltages as low as 75V and overvoltages as high as 147V without drawing battery backup power

Rotatable LCD Status Screen

- Large LCD screen shows real-time input voltage, overload, AVR and battery statuses
- Rotates for easy viewing in both horizontal and vertical installations
- Dimmer switch controls brightness level

AC Line, Tel/DSL and Ethernet Surge Suppression

- Surge suppression rating of 480 joules protects connected equipment and data from harmful power surges
- Built-in RJ-45 jacks protect single-line tel/DSL or network Ethernet connection

EMI/RFI Line Noise Filtering

• Removes electromagnetic and radio frequency interference that can disrupt or damage your equipment's performance

USB and DB9 Communication Ports and Free PowerAlert Software

- HID-compliant USB port integrates with built-in power management and auto-shutdown of Windows and Mac OS X
- USB and DB9 serial ports work with Tripp Lite PowerAlert software (available as free web download) to enable safe, unattended system shutdown and file saves during prolonged power failure

Flexible Installation Options

- NEMA 5-15P plug with 6-foot cord connects to any NEMA 5-15R socket
- Adapts to vertical or horizontal installation without special hardware
- Includes 2U brackets for rack-mount installation

Specifications

ОШТРИТ		
Output Volt Amp Capacity (VA)	1500	
Output kVA Capacity (kVA)	1.5	
Output Watt Capacity (Watts)	900	
Nominal Output Voltage(s) Supported	115V; 120V	
Frequency Compatibility	60 Hz	
Output Voltage Regulation (Line Mode)	-18%, +8%	
Output Voltage Regulation (Battery Mode)	115V (+/- 5%)	
Output Receptacles	(8) 5-15R	
Output AC Waveform (AC Mode)	Sine wave	
Output AC Waveform (Battery Mode)	PWM sine wave	
INPUT		





Rated input current (Maximum Load)	8.5A
Nominal Input Voltage(s) Supported	120V AC
UPS Input Connection Type	5-15P; Right-Angled
Input Circuit Breakers	10A
UPS Input Cord Length (ft.)	6
UPS Input Cord Length (m)	1.8
Recommended Electrical Service	15A 120V
Input Phase	Single-Phase
BATTERY	
Full Load Runtime (min.)	3.5 min. (900w)
Half Load Runtime (min.)	13 min. (450w)
DC System Voltage (VDC)	24
Battery Recharge Rate (Included Batteries)	Less than 4.5 hours from 10% to 90%
Expandable Runtime	No
VOLTAGE REGULATION	
Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147
Overvoltage Correction	Input voltages between 128 and 147 are reduced by 12%
Undervoltage Correction	Input voltages between 93 and 107 are boosted by 14%
Undervoltage Correction Severe Undervoltage Correction	Input voltages between 93 and 107 are boosted by 14% Input voltages between 75 and 92 are boosted by 30%
	Input voltages between 75 and 92 are boosted by 30%
Severe Undervoltage Correction	Input voltages between 75 and 92 are boosted by 30%
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON	Input voltages between 75 and 92 are boosted by 30% ITROLS Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display	Input voltages between 75 and 92 are boosted by 30% ITROLS Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches	Input voltages between 75 and 92 are boosted by 30% ITROLS Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation	Input voltages between 75 and 92 are boosted by 30% ITROLS Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation Audible Alarm	Input voltages between 75 and 92 are boosted by 30% ITROLS Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation Audible Alarm LED Indicators	Input voltages between 75 and 92 are boosted by 30% ITROLS Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION	Input voltages between 75 and 92 are boosted by 30% ITROLS Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions Front panel LCD display
Severe Undervoltage Correction USER INTERFACE, ALERTS & CON Front Panel LCD Display Switches Alarm Cancel Operation Audible Alarm LED Indicators SURGE / NOISE SUPPRESSION UPS AC Suppression Joule Rating UPS AC Suppression Response	Input voltages between 75 and 92 are boosted by 30% Backlighted LCD screen indicates input voltage, 5-bar battery charge level, overload, AVR, on battery and replace battery status; LCD screen rotates for rack/tower viewing 2 Switches control off/on power status and alarm-cancel/self-test operation; dimmer switch controls LCD brightness Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible alarm indicates power-failure and low-battery conditions Front panel LCD display



PHYSICAL		
Included Mounting Accessory Description	Pair of mounting ears enable tower and 2-4 post rackmount installation	
Installation Form Factors Supported with Included Accessories	Tower	
Primary Form Factor	Rackmount	
UPS Power Module Dimensions (hwd, in.)	3.5 x 17.25 x 10.5	
UPS Power Module Dimensions (hwd, cm)	8.9 x 43.8 x 26.7	
Rack Height (U Spaces)	2	
Maximum Device Depth (in.)	10.5	
Maximum Device Depth (cm)	26.7	
UPS Power Module Weight (lbs.)	29.4	
UPS Power Module Weight (kg)	13.3	
UPS Shipping Dimensions (hwd / in.)	7.5 x 15 x 21.5	
UPS Shipping Dimensions (hwd / cm)	19 x 38.1 x 54.6	
Shipping Weight (lbs.)	33.4	
Shipping Weight (kg)	15.2	
Cooling Method	Fan	
UPS Housing Material	ABS	
ENVIRONMENTAL		
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius	
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius	
Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	255	
AC Mode Efficiency Rating (100% Load)	92%	
COMMUNICATIONS		
Communications Interface	USB (HID enabled); DB9 Serial	
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions	
PowerAlert Software	Free download from www.tripplite.com	
Communications Cable	USB and DB9 Serial cabling included	
WatchDog Compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications	





LINE / BATTERY TRANSFER		
Transfer Time	4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	75	
High Voltage Transfer to Battery Power (Setpoint)	147	
SPECIAL FEATURES		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
CERTIFICATIONS		
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category B (EMI)	
WARRANTY		
Product Warranty Period (U.S. & Canada)	3-year limited warranty	
Product Warranty Period (Latin America)	3-year limited warranty	
Product Warranty Period (International)	2-year limited warranty	
Product Warranty Period (Mexico)	3-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance	

© 2016 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies:

http://www.tripplite.com/products/product-certification-agencies